



# MINI DIRECT FEED 250W SURFACE TRANSFORMER

The Mini answers the question, how small can it be? At 1.4 inches deep and 5.25 inches in diameter, it is the smallest 250 watt surface Monorail transformer in the industry. It installs similarly to our existing family of 250 watt transformers and practically disappears on the Monorail system.



### THE MINI

Truly minimalist design and the industry's smallest 250 watt surface transformer. Constructed of die-cast aluminum. Mounts to a standard 4" ceiling junction box with round plaster ring (provided by electrician). To be used with special standoff specifically designed for this transformer.

<b>MINI</b>	<b>LED</b>
<b>MODEL</b>	<b>TRANSDIRMNE250</b>
<b>FINISH</b>	<b>BZ bronze SC satin nickel</b>



<b>DIRECT FEED STANDOFF FOR MINI</b>	
<b>MODEL</b>	<b>HANGERDIRMN</b>
<b>FINISH</b>	<b>BZ bronze SC satin nickel</b>

TRANSFORMER	WATTAGE & TYPE	MODEL NUMBER	INPUT	OUTPUT	COMPATIBLE DIMMER*	COMPATIBLE STANDOFF
 <span style="float: right;"><b>LED</b></span>	12 volt / 250W Electronic Mini Direct Feed Single-Feed	TRANSDIRMNE250 (BZ, SC)	1x120VAC/2.5A	1x250W	Electronic Low-voltage v Dimmer 600W	Standoff for Mini Direct Feed

**LED** Indicates which transformers are compatible with LED fixtures

\*As a general rule when using LED fixtures we do not recommend using greater than 70% of specified maximum wattage on the transformer due to inrush current. For assistance, please contact our technical support department.